

BR-6473AX

Schnellinstallationsanleitung

03-2021 / v1.2

Edimax Technology Co., Ltd.

No. 278, Xinhua 1st Rd., Neihu Dist., Taipei City, Taiwan

Email: support@edimax.com.tw

Edimax Technology Europe B.V.

Fijenhof 2, 5652 AE Eindhoven, The Netherlands

Email: support@edimax.nl

Edimax Computer Company

530 Technology Drive Suite 100, Irvine, CA 92618, USA

Email: support@edimax.us

Inhalt

I. Produktinformationen	1
II. Verpackungsinhalt.....	2
II-1. Systemanforderungen.....	2
II-2. Hardwareübersicht	3
II-3. LED-Status	5
III. Hardwareinstallation.....	6
III-1. Zugangspunkt-Modus	7
III-2. Router-Modus	9
IV. Schnellkonfiguration	11
V. WPS.....	14
VI. Firmware-Upgrade	15
VII. Reset	17

I. Produktinformationen

Der Edimax BR-6473AX Smart Wi-Fi Zugangspunkt/Router mit Intel GRX350 (800MHz Dual-Core) und schnellen Dualband-Geschwindigkeiten von bis zu 574Mbps (2,4 GHz) und 2402Mbps (5 GHz) ist gut für Heimanwendungen geeignet.

Der BR-6473AX mit strahlformenden + 4 internen Antennen bietet eine schnelle und zuverlässige Wi-Fi-Abdeckung mit großer Reichweite in jeder Ecke Ihres Hauses.

Mit der einfachen und intuitiven Web-Benutzeroberfläche lässt sich der Zugangspunkt/Router einfach einrichten und über den Browser oder das Smartphone fernbedienen.

Alle unterstützenden Dokumente finden Sie über den folgenden Link oder den QR-Code:

<https://www.edimax.com/download>




(Geben Sie nach Ihrem Besuch der offiziellen Edimax-Website die Modellnummer „BR-6473AX“ in das Suchfeld ein, um nach diesem Produkt zu suchen.)

Download


To select your product and find related download materials, enter the model number into the search box on the right side or follow the simple steps below:

*Feel free to contact us anytime if you need help or if you can't find your product.

A screenshot of a web search interface. It features a search bar with the placeholder text "Model no." and a magnifying glass icon on the right. Below the search bar, there is a link that says "How do I find the model number?". The entire search area is highlighted with a red rectangular border.

II. Verpackungsinhalt


Bevor Sie dieses Produkt benutzen, überprüfen Sie bitte, ob irgendetwas in der Verpackung fehlt, und wenden Sie sich an Ihren Händler, um fehlende Teile zu melden.




BR-6473AX



Schnellinstallationsanlei



Netzadapter (12V)




Ethernetkabel

II-1. Systemanforderungen

- Vorhandenes Kabel/DSL-Modem & Router
- Computer mit Web-Browser zur Zugangspunkt-Konfiguration

II-2. Hardwareübersicht



Nr.	Beschreibung
1	LED (2,4G, 5G, WPS, LAN1, LAN2, LAN3, LAN4, WAN, POWER)
2	Umschalter (Router- und Zugangspunkt-Modus)
3	WPS-Taste
4	RESET-Taste
5	LAN4-Anschluss
6	LAN3-Anschluss
7	LAN2-Anschluss
8	LAN1-Anschluss
9	WAN-Anschluss
10	DC-Netzbuchse

II-3. LED-Status

Funktion	Farbe	Status	Beschreibung
2,4GH & 5GHz	Blau	An	Internetverbindung ist bereit.
		Aus	WLAN ist nicht aktiv.
		Blinkend	Aktiv. Senden oder Empfangen von Daten.
WPS	Blau	Blinkend	WPS-Verbindung errichtet. (Die WPS-LED blinkt 2 Sekunden lang, wenn eine erfolgreiche Verbindung hergestellt wurde.)
LAN	Blau	An	LAN-Anschluss ist angeschlossen.
		Aus	LAN ist nicht angeschlossen.
WAN	Blau	An	WAN-Anschluss ist angeschlossen.
		Aus	WAN-Port ist nicht angeschlossen oder nicht mit dem Internet verbunden.
Power	Rot	Blinkend	Aktualisieren der Firmware oder Zurücksetzen.
	Grün	An	Router-Modus. (Stromversorgung an)
	Blau	An	Zugangspunkt-Modus (AP-Modus). (Stromversorgung an)


III. Hardwareinstallation

Dieser Abschnitt führt Sie durch die Schritte zur Einrichtung des BR-6473AX für den Betrieb im Zugangspunkt- und Router-Modus.

Sie können die Betriebsart über den Umschalter an der Rückseite des BR-6473AX ändern.

Stellen Sie den Umschalter auf die gewünschte Betriebsart (Zugangspunkt- bzw. Router-Modus).


HINWEIS: Ziehen Sie erst den Netzstecker, bevor Sie die Betriebsart ändern.




III-1. Zugangspunkt-Modus

1. Stellen Sie den Umschalter des BR-6473AX auf den Zugangspunkt-Modus.
2. Stecken Sie das AC-Netzteil in die Buchse des Zugangspunkts/Routers und das andere Ende in eine Steckdose.

Hinweis: Stellen Sie sicher, dass die „POWER“-LED Blau leuchtet (Zugangspunkt-Modus). Falls nicht, ist das Gerät nicht ordnungsgemäß angeschlossen.



3. Verbinden Sie Ihren Router über ein Ethernetkabel mit dem „LAN“-Anschluss am BR-6473AX.




HINWEIS: Stellen Sie sicher, dass die „LAN“-LED **BLAU** leuchtet.


III-2. Router-Modus

1. Stellen Sie den Umschalter des BR-6473AX auf den Router-Modus.
2. Stecken Sie das AC-Netzteil in die Buchse des Zugangspunkts/Routers und das andere Ende in eine Steckdose.

Hinweis: Stellen Sie sicher, dass die „POWER“-LED Grün leuchtet (Router-Modus). Falls nicht, ist das Gerät nicht ordnungsgemäß angeschlossen.



3. Verbinden Sie Ihr Modem über ein Ethernetkabel mit dem „WAN“-Anschluss am BR-6473AX.



HINWEIS: Stellen Sie sicher, dass die „WAN“-LED **BLAU** leuchtet.

IV. Schnellkonfiguration


Dieser Schnellinstallationsabschnitt wird Sie dabei unterstützen, Ihren Zugangspunkt/Router in seinem standardmäßigen Zugangspunkt-Modus einzurichten und seine Grundeinstellungen zu konfigurieren.

Befolgen Sie bitte die nachfolgenden Schritte:


1. Den Standardbenutzernamen „admin“ und das spezifische 8-stellige Standardpasswort „XXXXXXXX“ Ihres Routers finden Sie auf dem Geräteaufkleber.



HINWEIS: Wenn Sie iOS 11 oder eine neuere Version verwenden, können Sie Ihr Smartphone ganz einfach über den QR-Code auf dem Geräteaufkleber mit dem Zugangspunkt/Router verbinden.



2. Öffnen Sie einen Internetbrowser und geben Sie die Standard-IP 192.168.2.1 ein (im Zugangspunkt-Modus).
3. Sie werden aufgefordert, einen Benutzernamen und ein Passwort einzugeben. Geben Sie den Benutzernamen und das Passwort ein. Klicken Sie auf die Taste „Sign in“ (Anmelden).



Sign in


http://192.168.2.1


Your connection to this site is not private

Username

Password


4. Erstmalige Benutzer setzen bitte den 2.4G SSID/ 5G SSID-Namen und das entsprechende Passwort zurück.




 **Changing SSID & Password** [Home > Change Password](#)

Note: For Network Security, Please Change Your WiFi Password and SSID (Network Name) Before Using BR-6473AX.


2.4G SSID

2.4G Password 

5G SSID

5G Password 


5. Warten Sie 60 Sekunden lang.



V. WPS

WPS ist eine einfache Methode, um Verbindungen zwischen WPS-fähigen Geräten herzustellen. Sie können die WPS-Taste am BR-6473AX verwenden, um die WPS-Funktion des Zugangspunktes/Routers zu aktivieren.


1. Halten Sie die WPS-Taste 2 Sekunden lang gedrückt, um WPS zu aktivieren.
2. Die WPS-Funktion Ihres Zugangspunktes/Routers ist aktiviert, wenn die WPS-LED **BLAU** blinkt.




VI. Firmware-Upgrade

Sie können die Firmware des Zugangspunktes/Routers entweder durch OTA oder über ein manuelles Update aktualisieren. Bitte befolgen Sie die nachfolgenden Schritte, um die Firmware zu aktualisieren.

1. Klicken Sie auf die Schaltfläche „Administration“ (Verwaltung).




2. Klicken Sie auf „Firmware Upgrade“.




3. Klicken Sie auf „Check Version“ (Version prüfen), um zu überprüfen, ob die aktuelle Firmware auf dem neuesten Stand ist.

Wählen Sie „Local File“ (Lokale Datei), um die Firmware-Datei auf den Zugangspunkt/Router hochzuladen.

Wählen Sie „Online Upgrade“, um die Firmware über OTA zu aktualisieren.



4. Klicken Sie auf die Schaltfläche „Upgrade“ und „OK“, um die Aktualisierung der Firmware zu starten.




VII. Reset

Wenn Sie mit Ihrem Zugangspunkt/Router auf Probleme stoßen, können Sie das Gerät auf die Werksstandardeinstellungen zurücksetzen.

Es gibt 2 Methoden, um das Gerät zurückzusetzen.

Zurücksetzen der Hardware:


1. Halten Sie die Reset-Taste am Zugangspunkt/Router mindestens 5 Sekunden lang gedrückt und lassen Sie sie dann los. Bitte warten Sie ein paar Minuten, bis der Zugangspunkt/Router neu startet. Wenn das Gerät neu startet, werden alle Einstellungen zurückgesetzt.
2. Warten Sie, bis der Zugangspunkt/Router neu gestartet wird. Der Zugangspunkt/Router ist bereit für die Einrichtung, wenn die Power-LED **ROT** blinkt.




Webseiten-Schnittstelle:

Befolgen Sie bitte die nachfolgenden Schritte, um das Gerät über die Webseite zurückzusetzen.


1. Klicken Sie auf die Schaltfläche „Administration“ (Verwaltung).



2. Klicken Sie auf die Schaltfläche „Backup and Restore“ (Sicherung und Wiederherstellung).



3. Klicken Sie auf die Schaltflächen „Reset“ und „OK“, um den Zugangspunkt/Router auf die Werkseinstellungen zurückzusetzen.



COPYRIGHT

Copyright © Edimax Technology Co., Ltd. all rights reserved. No part of this publication may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language, in any form or by any means, electronic, mechanical, magnetic, optical, chemical, manual or otherwise, without the prior written permission from Edimax Technology Co., Ltd.

Edimax Technology Co., Ltd. makes no representations or warranties, either expressed or implied, with respect to the contents hereof and specifically disclaims any warranties, merchantability, or fitness for any particular purpose. Any software described in this manual is sold or licensed as is. Should the programs prove defective following their purchase, the buyer (and not this company, its distributor, or its dealer) assumes the entire cost of all necessary servicing, repair, and any incidental or consequential damages resulting from any defect in the software. Edimax Technology Co., Ltd. reserves the right to revise this publication and to make changes from time to time in the contents hereof without the obligation to notify any person of such revision or changes.

The product you have purchased and the setup screen may appear slightly different from those shown in this QIG. The software and specifications are subject to change without notice. Please visit our website www.edimax.com for updates. All brand and product names mentioned in this manual are trademarks and/or registered trademarks of their respective holders.

	AT	BE	BG	HR	CY	CZ	DK
	EE	FI	FR	DE	EL	HU	IE
	IT	LV	LT	LU	MT	NL	PL
	PT	RO	SK	SI	ES	SE	UK

The device is restricted to indoor use only when operating in the 5150 to 5350 MHz frequency range.

Federal Communication Commission Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

1. Reorient or relocate the receiving antenna.
2. Increase the separation between the equipment and receiver.
3. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
4. Consult the dealer or an experienced radio technician for help.

FCC Caution

This device and its antenna must not be co-located or operating in conjunction with any other antenna or transmitter. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any changes or modifications not expressly approved by the party responsible for compliance could void the authority to operate equipment.

Federal Communications Commission (FCC) Radiation Exposure Statement

This equipment complies with FCC radiation exposure set forth for an uncontrolled environment. In order to avoid the possibility of exceeding the FCC radio frequency exposure limits, human proximity to the antenna shall not be less than 2.5cm (1 inch) during normal operation.

The equipment version marketed in US is restricted to usage of the channels 1-11 only. This equipment is restricted to **indoor** use when operated in the 5.15 to 5.25 GHz frequency range.

RED Compliance Statement

Compliance with 2014/53/EU Radio Equipment Directive (RED)

In accordance with Article 10.8(a) and 10.8(b) of the RED, the following table provides information on the frequency bands used and the maximum RF transmit power of the product for sale in the EU:

Frequency range (MHz)	Max. transmit power (dBm)
2400-2483.5	19.98 dBm
5150-5250	22.99 dBm
5250-5350	22.99 dBm
5470-5725	29.98 dBm

A simplified DoC shall be provided as follows: Article 10(9)

Hereby, Edimax Technology Co., Ltd. declares that the radio equipment type **AX3000 Dual-Band Router** is in compliance with Directive 2014/53/EU

The full text of the EU declaration of conformity is available at the following internet address: <http://www.edimax.com/edimax/global/>

Safety

This equipment is designed with the utmost care for the safety of those who install and use it. However, special attention must be paid to the dangers of electric shock and static electricity when working with electrical equipment. All guidelines of this and of the computer manufacture must therefore be allowed at all times to ensure the safe use of the equipment.

EU Countries Intended for Use

The ETSI version of this device is intended for home and office use in Austria, Belgium, Bulgaria, Cyprus, Czech, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Turkey, and United Kingdom. The ETSI version of this device is also authorized for use in EFTA member states: Iceland, Liechtenstein, Norway, and Switzerland.

EU Countries Not Intended for Use

None

EU Declaration of Conformity

- English:** This equipment is in compliance with the essential requirements and other relevant provisions of Directive 2014/53/EU, 2014/35/EU.
- Français:** Cet équipement est conforme aux exigences essentielles et autres dispositions de la directive 2014/53/EU, 2014/35/EU.
- Čeština:** Toto zařízení je v souladu se základními požadavky a ostatními příslušnými ustanoveními směrnic 2014/53/EU, 2014/35/EU.
- Polski:** Urządzenie jest zgodne z ogólnymi wymaganiami oraz szczególnymi warunkami określonymi Dyrektywą UE 2014/53/EU, 2014/35/EU.
- Română:** Acest echipament este în conformitate cu cerințele esențiale și alte prevederi relevante ale Directivei 2014/53/UE, 2014/35/UE.
- Русский:** Это оборудование соответствует основным требованиям и положениям Директивы 2014/53/EU, 2014/35/EU.
- Magyar:** Ez a berendezés megfelel az alapvető követelményeknek és más vonatkozó irányelveknek (2014/53/EU, 2014/35/EU).
- Türkçe:** Bu cihaz 2014/53/EU, 2014/35/EU direktifleri zorunlu istekler ve diğer hükümlerle ile uyumludur.
- Українська:** Обладнання відповідає вимогам і умовам директиви 2014/53/EU, 2014/35/EU.
- Slovenčina:** Toto zariadenie spĺňa základné požiadavky a ďalšie príslušné ustanovenia smerníc 2014/53/EU, 2014/35/EU.
- Deutsch:** Dieses Gerät erfüllt die Voraussetzungen gemäß den Richtlinien 2014/53/EU, 2014/35/EU.
- Español:** El presente equipo cumple los requisitos esenciales de la Directiva 2014/53/EU, 2014/35/EU.
- Italiano:** Questo apparecchio è conforme ai requisiti essenziali e alle altre disposizioni applicabili della Direttiva 2014/53/EU, 2014/35/UE.
- Nederlands:** Dit apparaat voldoet aan de essentiële eisen en andere van toepassing zijnde bepalingen van richtlijn 2014/53/EU, 2014/35/EU.
- Português:** Este equipamento cumpre os requisitos essenciais da Directiva 2014/53/EU, 2014/35/EU.
- Norsk:** Dette utstyret er i samsvar med de viktigste kravene og andre relevante regler i Direktiv 2014/53/EU, 2014/35/EU.
- Svenska:** Denna utrustning är i överensstämmelse med de väsentliga kraven och övriga relevanta bestämmelser i direktiv 2014/53/EU, 2014/35/EU.
- Dansk:** Dette udstyr er i overensstemmelse med de væsentligste krav og andre relevante forordninger i direktiv 2014/53/EU, 2014/35/EU.
- suomen kieli:** Tämä laite täyttää direktiivien 2014/53/EU, 2014/35/EU. oleelliset vaatimukset ja muut asiaankuuluvat määräykset.

FOR USE IN **AT BE CY CZ DK EE FI FR DE GR HU**
IE IT LV LT LU MT NL PL PT SK SI ES SE
GB IS LI NO CH BG RO RU TR UA



WEEE Directive & Product Disposal



At the end of its serviceable life, this product should not be treated as household or general waste. It should be handed over to the applicable collection point for the recycling of electrical and electronic equipment, or returned to the supplier for disposal.

Declaration of Conformity

We, Edimax Technology Co., Ltd., declare under our sole responsibility, that the equipment described below complies with the requirements of the European Radio Equipment directives.

Equipment: AX3000 Dual-Band Router

Model No.: BR-6473AX

The following European standards for essential requirements have been followed:

Directives 2014/53/EU

Spectrum : EN 300 328 V2.1.1 (2016-11)
EN 301 893 V2.1.1 (2017-05)

EMC : EN 301 489-1 V2.2.0 (2017-03), Class B
EN 301 489-17 V3.2.0 (2017-03)
EN 55032:2015/AC:2016 Class B
EN 55035:2017

EMF : EN 62311:2008 and EN50665:2017

Safety (LVD) : IEC 62368-1:2014 (2nd Edition) and/or EN 62368-1:2014+A11:2017

Edimax Technology Europe B.V.
Fijenhof 2,
5652 AE Eindhoven,
The Netherlands

a company of :
Edimax Technology Co., Ltd.
No. 278, Xinhua 1st Rd.,
Neihu Dist., Taipei City,
Taiwan

Signature:

Printed Name: David Huang
Title: Director
Edimax Technology Europe B.V.



Date of Signature: Dec., 2019

Signature:

A handwritten signature in black ink, appearing to read 'Albert Chang', written over a horizontal line.

Printed Name:

Albert Chang

Title:

Director

Edimax Technology Co., Ltd.

Notice According to GNU General Public License Version 2

This product includes software that is subject to the GNU General Public License version 2. The program is free software and distributed without any warranty of the author. We offer, valid for at least three years, to give you, for a charge no more than the costs of physically performing source distribution, a complete machine-readable copy of the corresponding source code.

Das Produkt beinhaltet Software, die den Bedingungen der GNU/GPL-Version 2 unterliegt. Das Programm ist eine sog. „Free Software“, der Autor stellt das Programm ohne irgendeine Gewährleistungen zur Verfügung. Wir bieten Ihnen für einen Zeitraum von drei Jahren an, eine vollständige maschinenlesbare Kopie des Quelltextes der Programme zur Verfügung zu stellen – zu nicht höheren Kosten als denen, die durch den physikalischen Kopiervorgang anfallen.

GNU GENERAL PUBLIC LICENSE

Version 2, June 1991

Copyright (C) 1989, 1991 Free Software Foundation, Inc. 51 Franklin Street, Fifth Floor, Boston, MA 02110-1301, USA
Everyone is permitted to copy and distribute verbatim copies of this license document, but changing it is not allowed.

Preamble

The licenses for most software are designed to take away your freedom to share and change it. By contrast, the GNU General Public License is intended to guarantee your freedom to share and change free software--to make sure the software is free for all its users. This General Public License applies to most of the Free Software Foundation's software and to any other program whose authors commit to using it. (Some other Free Software Foundation software is covered by the GNU Lesser General Public License instead.) You can apply it to your programs, too.

When we speak of free software, we are referring to freedom, not price. Our General Public Licenses are designed to make sure that you have the freedom to distribute copies of free software (and charge for this service if you wish), that you receive source code or can get it if you want it, that you can change the software or use pieces of it in new free programs; and that you know you can do these things.

To protect your rights, we need to make restrictions that forbid anyone to deny you these rights or to ask you to surrender the rights. These restrictions translate to certain responsibilities for you if you distribute copies of the software, or if you modify it.

For example, if you distribute copies of such a program, whether gratis or for a fee, you must give the recipients all the rights that you have. You must make sure that they, too, receive or can get the source code. And you must show them these terms so they know their rights.

We protect your rights with two steps: (1) copyright the software, and (2) offer you this license which gives you legal permission to copy, distribute and/or modify the software.

Also, for each author's protection and ours, we want to make certain that everyone understands that there is no warranty for this free software. If the software is modified by someone else and passed on, we want its recipients to know that what they have is not the original, so that any problems introduced by others will not reflect on the original authors' reputations.

Finally, any free program is threatened constantly by software patents. We wish to avoid the danger that redistributors of a free program will individually obtain patent licenses, in effect making the program proprietary. To prevent this, we have made it clear that any patent must be licensed for everyone's free use or not licensed at all.

The precise terms and conditions for copying, distribution and modification follow.

TERMS AND CONDITIONS FOR COPYING, DISTRIBUTION AND MODIFICATION

0. This License applies to any program or other work which contains a notice placed by the copyright holder saying it may be distributed under the terms of this General Public License. The "Program", below, refers to any such program or work, and a "work based on the Program" means either the Program or any derivative work under copyright law: that is to say, a work containing the Program or a portion of it, either verbatim or with modifications and/or translated into another language. (Hereinafter, translation is included without limitation in the term "modification".) Each licensee is addressed as "you".

Activities other than copying, distribution and modification are not covered by this License; they are outside its scope. The act of running the Program is not restricted, and the output from the Program is covered only if its contents constitute a work based on the Program (independent of having been made by running the Program). Whether that is true depends on what the Program does.

1. You may copy and distribute verbatim copies of the Program's source code as you receive it, in any medium, provided that you conspicuously and appropriately publish on each copy an appropriate copyright notice and disclaimer of warranty; keep

intact all the notices that refer to this License and to the absence of any warranty; and give any other recipients of the Program a copy of this License along with the Program.

You may charge a fee for the physical act of transferring a copy, and you may at your option offer warranty protection in exchange for a fee.

2. You may modify your copy or copies of the Program or any portion of it, thus forming a work based on the Program, and copy and distribute such modifications or work under the terms of Section 1 above, provided that you also meet all of these conditions:

- a) You must cause the modified files to carry prominent notices stating that you changed the files and the date of any change.
- b) You must cause any work that you distribute or publish, that in whole or in part contains or is derived from the Program or any part thereof, to be licensed as a whole at no charge to all third parties under the terms of this License.
- c) If the modified program normally reads commands interactively when run, you must cause it, when started running for such interactive use in the most ordinary way, to print or display an announcement including an appropriate copyright notice and a notice that there is no warranty (or else, saying that you provide a warranty) and that users may redistribute the program under these conditions, and telling the user how to view a copy of this License. (Exception: if the Program itself is interactive but does not normally print such an announcement, your work based on the Program is not required to print an announcement.)

These requirements apply to the modified work as a whole. If identifiable sections of that work are not derived from the Program, and can be reasonably considered independent and separate works in themselves, then this License, and its terms, do not apply to those sections when you distribute them as separate works. But when you distribute the same sections as part of a whole which is a work based on the Program, the distribution of the whole must be on the terms of this License, whose permissions for other licensees extend to the entire whole, and thus to each and every part regardless of who wrote it.

Thus, it is not the intent of this section to claim rights or contest your rights to work written entirely by you; rather, the intent is to exercise the right to control the distribution of derivative or collective works based on the Program.

In addition, mere aggregation of another work not based on the Program with the Program (or with a work based on the Program) on a volume of a storage or distribution medium does not bring the other work under the scope of this License.

3. You may copy and distribute the Program (or a work based on it, under Section 2) in object code or executable form under the terms of Sections 1 and 2 above provided that you also do one of the following:

- a) Accompany it with the complete corresponding machine-readable source code, which must be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange; or,
- b) Accompany it with a written offer, valid for at least three years, to give any third party, for a charge no more than your cost of physically performing source distribution, a complete machine-readable copy of the corresponding source code, to be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange; or,
- c) Accompany it with the information you received as to the offer to distribute corresponding source code. (This alternative is allowed only for noncommercial distribution and only if you received the program in object code or executable form with such an offer, in accord with Subsection b above.)

The source code for a work means the preferred form of the work for making modifications to it. For an executable work, complete source code means all the source code for all modules it contains, plus any associated interface definition files, plus the scripts used to control compilation and installation of the executable. However, as a special exception, the source code distributed need not include anything that is normally distributed (in either source or binary form) with the major components (compiler, kernel, and so on) of the operating system on which the executable runs, unless that component itself accompanies the executable.

If distribution of executable or object code is made by offering access to copy from a designated place, then offering equivalent access to copy the source code from the same place counts as distribution of the source code, even though third parties are not compelled to copy the source along with the object code.

4. You may not copy, modify, sublicense, or distribute the Program except as expressly provided under this License. Any attempt otherwise to copy, modify, sublicense or distribute the Program is void, and will automatically terminate your rights under this License. However, parties who have received copies, or rights, from you under this License will not have their licenses terminated so long as such parties remain in full compliance.

5. You are not required to accept this License, since you have not signed it. However, nothing else grants you permission to modify or distribute the Program or its derivative works. These actions are prohibited by law if you do not accept this License. Therefore, by modifying or distributing the Program (or any work based on the Program), you indicate your acceptance of this License to do so, and all its terms and conditions for copying, distributing or modifying the Program or works based on it.

6. Each time you redistribute the Program (or any work based on the Program), the recipient automatically receives a license from the original licensor to copy, distribute or modify the Program subject to these terms and conditions. You may not impose any further restrictions on the recipients' exercise of the rights granted herein. You are not responsible for enforcing compliance by third parties to this License.

7. If, as a consequence of a court judgment or allegation of patent infringement or for any other reason (not limited to patent issues), conditions are imposed on you (whether by court order, agreement or otherwise) that contradict the conditions of this License, they do not excuse you from the conditions of this License. If you cannot distribute so as to satisfy simultaneously your obligations under this License and any other pertinent obligations, then as a consequence you may not distribute the Program at all. For example, if a patent license would not permit royalty-free redistribution of the Program by all those who receive copies directly or indirectly through you, then the only way you could satisfy both it and this License would be to refrain entirely from distribution of the Program.

If any portion of this section is held invalid or unenforceable under any particular circumstance, the balance of the section is intended to apply and the section as a whole is intended to apply in other circumstances.

It is not the purpose of this section to induce you to infringe any patents or other property right claims or to contest validity of any such claims; this section has the sole purpose of protecting the integrity of the free software distribution system, which is implemented by public license practices. Many people have made generous contributions to the wide range of software distributed through that system in reliance on consistent application of that system; it is up to the author/donor to decide if he or she is willing to distribute software through any other system and a licensee cannot impose that choice.

This section is intended to make thoroughly clear what is believed to be a consequence of the rest of this License.

8. If the distribution and/or use of the Program is restricted in certain countries either by patents or by copyrighted interfaces, the original copyright holder who places the Program under this License may add an explicit geographical distribution limitation excluding those countries, so that distribution is permitted only in or among countries not thus excluded. In such case, this License incorporates the limitation as if written in the body of this License.

9. The Free Software Foundation may publish revised and/or new versions of the General Public License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns.

Each version is given a distinguishing version number. If the Program specifies a version number of this License which applies to it and "any later version", you have the option of following the terms and conditions either of that version or of any later version published by the Free Software Foundation. If the Program does not specify a version number of this License, you may choose any version ever published by the Free Software Foundation.

10. If you wish to incorporate parts of the Program into other free programs whose distribution conditions are different, write to the author to ask for permission. For software which is copyrighted by the Free Software Foundation, write to the Free Software Foundation; we sometimes make exceptions for this. Our decision will be guided by the two goals of preserving the free status of all derivatives of our free software and of promoting the sharing and reuse of software generally.

NO WARRANTY

11. BECAUSE THE PROGRAM IS LICENSED FREE OF CHARGE, THERE IS NO WARRANTY FOR THE PROGRAM, TO THE EXTENT PERMITTED BY APPLICABLE LAW. EXCEPT WHEN OTHERWISE STATED IN WRITING THE COPYRIGHT HOLDERS AND/OR OTHER PARTIES PROVIDE THE PROGRAM "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE PROGRAM IS WITH YOU. SHOULD THE PROGRAM PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION.

12. IN NO EVENT UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY WHO MAY MODIFY AND/OR REDISTRIBUTE THE PROGRAM AS PERMITTED ABOVE, BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE PROGRAM (INCLUDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY YOU OR THIRD PARTIES OR A FAILURE OF THE PROGRAM TO OPERATE WITH ANY OTHER PROGRAMS), EVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.