



Sitecom Product Specifications Sheet

Product code: LN-307
Product: Parallel Printer server
EAN Code: 8716502005178
Qty. masterpack/carton: 5/10

Product weight: 500g
Product dimensions: 82 x 57 x 25 mm
Gift box weight: 0.68 kg
Gift box dimensions: 210 x 150 x 70 mm
Masterpack Weight: 4.4 Kg
Masterpack Dimensions: 35.5 x 19 x 26 cm
Carton weight: 8.8 Kg
Carton dimensions: 40 x 36 x 27 cm

This Network Printer Server makes it possible for you to add a parallel printer to your network simply and quickly. This printer can then be used by any user from different computers in the network. The Network Printer Server is fitted with a network port (10/100 Mbps) so that you can connect it to any network device such as a hub, switch or a network card. Thanks to the supplied Wizard, the printer server is easy to install and because it supports the most important protocols, the printer server can be easily integrated in almost any network. • Works under the TCP/IP, IPX/SPX, NetBEUI protocols • BiAdmin programme for configuration/management • Automatic IP setting • Supports Internet Printing Protocol



**Box content :**

- Network Printer Server - Parallel
- User manual
- Driver CD

System Requirements:

- Windows 98SE/ME/2000/XP
- Parallel printer
- Free network port on Hub, Switch or PC

Key features:

- Automatic IP setting
- Internet Printing
- Easy configuration & management
- Diagnostics
- Firmware Upgradeable

Technical specifications:

- Network Interface
 - 10BaseT/100BaseTx, Auto-sensing
 - Printer Connection
 - IEEE1284 compliant (Nibble/Byte mode support). Type B Centronics
 - Protocol Support
 - TCP/IP, NetBEUI, AppleTalk, IPX/SPX
 - NOS Support
 - Windows 95/98/2000/NT/Me/XP, Macintosh (OS 9.x and higher), UNIX,
 - Netware 3.x/4.x/5.x
 - Printing methods
 - PTP (Peer-to-Peer) over TCP/IP or NetBEUI protocol, Windows LPD printing,
 - SMB printing (via NetBEUI or TCP/IP protocol), IPP (Internet Printing Protocol),
 - Macintosh LaserWriter Chooser (EtherTalk)
 - NetWare NDPS LPR Printing, NetWare 3.1x (Bindery mode), 4.x (Bindery and NDS mode), 5.0 (Bindery, NDS, and NDPS in legacy mode)
 - Management Tools
 - BiAdmin (Windows Application), Web-based management (HTTP)
 - PC-based SNMP applications, FTP, Telenet
 - LED -10BaseT, 100BaseTx, Status, Error
 - Diagnostic button - Diagnostic Printing & Reset to Factory Default
 - Power Supply - 9V/500mA
 - Emission -FCC / CE / VCCI/C-Tick
-