## **BMC-config Usage Instructions**

Note this software is only for König SAS-DVRODR3x cameras, which are identical to SG880MK-xmHD cameras

- 1, Format your SD card
- 2, Connect the camera to your PC, open the BMC-config,

P BIC CONFIG	N 100 100 100 100 100 100 100 100 100 10
Products	
	Select Product MG982K-10M ▼ Remember My Choice OK ( <u>Y</u> ) EXIT ( <u>N</u> )

choose the model for camera

3, Select your country and SIM card operator

BEC CONFIG : For EG9	82K-10H
Boly Media Com	munications Co., Ltd. (BMC
	nternet Setting
Select Country	Select Operator
Australia	China-Mobile
Austria	China-Unicom
Canada	China-Unicom-3G
Chech	Others
China	
Check WAP / In	ternet Paramaters ( <u>L</u> )

4, Then "check WAP/Internet Parameters" to see if these parameters are right. If you use an SSL email as sending email, please click "Advanced" button to mark it.

VAP / Internet Paramaters	
Current WAP / Internet Paramaters As F	Follows, You Can Modify Highlighted 4 Items If Necessary ! Internet Setting
MMS URL : http://mmsc.monternet.com	SEND EMAIL SERVER : smtp.bolymedia.com
MMS APN : cmwap PORT : 80	GPRS APN : cmnet SEND PORT : 80
MMS IP : 10 . 0 . 0 . 172	GPRS ACCOUNT :
ACCOUNT :	GPRS PASS/VORD :
PASSWORD :	SEND EMAIL ADDRESS : bolyguard@bolymedia.com
CLEAR PARAMATERS (C)	SEND EMAIL PASS/VORD :
ок Ф	Cancel ( <u>N</u> )

WAP / Inte Select Country	rnet Setting Select Operator	Camera Setting Click "Default Setting" button if you
Australia Austria Canada Chech China	China-Mobile China-Unicom China-Unicom-3G Others	don't know how to modify camera Default Setting (D)
Check WAP / Inter	net Parameters ( <u>L)</u>	Change Setting ( <u>C</u> )
aters		E
/ Internet Parameters As I	Follows, You Can Modify	Highlighted 4 Items If Necessary !
AP Setting		Internet Setting
imsc.monternet.com	SEND EMAIL S	ERVER :  smtp.bolymedia.com
PORT : 8	0 GP	RS APN : cmnet PORT : 80
. 0 . 0 . 172	GPRS AC	COUNT :
Advand	ed Setup	
EAR PARAMETER	TP Server	SL (S)
		ancel (N) Advanced 00

5, If your country or SIM card operator is not in the list, try to find "Others", then input the parameters you need.

Sel Switzerla UK Ukraine USA Others	ect Country	Select Opera	itor	Just kno	: click " w how t	Default Setting" butt to modify camera pa Default Setting ( <u>I</u>	on if you don't aramaters ! 2)	
/ Intern	et Paramaters							
MMS LIBL •	P WAP Setting	lease Input User-De	efined WAP / In	ternet	Parama	aters Here! Internet Setting —		
MMS APN :		PORT :		GPRS	APN :		SEND PORT :	
MMS IP :			GPRS	ACCO	OUNT :	, 		
ACCOUNT :			GPRS F	ASSV	/ORD :			
ASSWORD :			send emai	L ADD	RESS :			
	CLEAR PARAN	IATERS ( <u>C</u> )	SEND EMAIL P	PASS\/	/ORD :			
		OK (Y)			Cancel	N		

WAP / Inte	rnet Setting			— Camera Setting	
Select Country	Select Operat	or	Just click "Default Setting" button if you don't		n if you don't
Canada A Chech China China HongKong Cyprus V	China-Mobile China-Unicom China-Unicom-3G Others			Default Setting (D)	
VAP / Internet Paramaters					
	Please Input User-De	efined WAP / I	Internet Parama	iters Here!	
WAP Setting				Internet Setting —	
MMS URL :		SEND EN	MAIL SERVER :		
MMS APN :	PORT :		GPRS APN :		SEND PORT :
MMS IP :		GPF	RS ACCOUNT :		
ACCOUNT :		GPRS	PASSWORD :		
PASSWORD :		SEND EM	AIL ADDRESS :		
CLEAR PARA	AMATERS ( <u>C</u> )	SEND EMAIL	PASSWORD :		
OK (Y) Cancel (N)					

6, It is suggested to use default settings when you first use the application software.

Boly Media Com	munications Co., Ltd. (BMC)	
	ternet Setting	Camera Setting
Select Country	Select Operator	Just click "Default Setting" button if you don't
Australia	China-Mobile	know how to modify camera paramaters !
Austria 📒	China-Unicom	
Canada	China-Unicom-3G	Default Setting ( <u>D</u> )
Chech	Others	
China Check WAP / Int	BIC TIPS	hange Setting (C)
dmin Number :	Set all camera param	aters to default ?

## 7, "Changing Setting" is for your customized.

WAP / Internet Setting		Camera Setting		
Select Country Select Operator		Just click "Default Setting" button if you don't		
Australia China	a-Mobile	know how to modify camera paramaters !		
Canada China	a-Unicom-3G	Default Setting (D)		
Chech Othe	rs			
Check WAP / Internet Par	amaters ( <u>L</u> )	Change Setting ( <u>C</u> )		
iera Setting				
Language English 💌 Camera M	ode Photo 💌 Sec	urity Mode OFF 💌 Camera Position OFF 💌		
Time Lapse OFF 💌 PIR Trigg	er Normal 💌 PII	R Interval 5 Sec 💌 SMS Control OFF 💌		
Photo Size 5M 💌 Photo Bu	rst 🛛 1 Photo 💌 Vi	deo Size 1280*720 Video Length 10 Sec 💌		
Game Call OFF 💽 H: 00 💌 M: 00 💌 Replay Time OFF 🛒 Set Clock : (SYSTEM TIME) 🗹				
Add Audio You can click the left butto	n to add audio file if Gam	neCall is ON ! 2014- 7-24 💌 9:37:17 😴		
Work Hour OFF 💽 Start Tin	ne 00 🔽 : 0	0 💌 Stop Time 00 💌 : 00 💌		
	Send To	Send Mode		
🗹 Select All 🛛 🗹 Sunday	Phone [MMS]	Manual		
🔽 Monday 🔽 Tuesday	C Email [MMS]	◯ Daily Report Send Time : 00 🔽 : 00 🔽		
🔽 Wednesday 🔽 Thursday	C Email [GPRS]	C Instant Max Number : 0		
🔽 Friday 🔽 Saturday	C Call	C Off		
	ок М	Cancel ( <u>N</u> )		

8, The default set for Game call is Off, change it to On and fill in when you want it to play if you want to use this function.

## Then select the audio to add in.

Game Call     ON     H:     18     M:     00     Replay Time       Add Audio     You can click the left button to add audio file if GameCall is	Image:
ля ? 🛛	▼ Stop Time 00 ▼ : 00 ▼
查找范围 (I): 🔁 Video 🔽 🗧 🖆 🎫	Send Mode
AVDI00001. WAY	lanual
	aily Report Send Time : 00 💌 : 00 💌
	stant Max Number : 0 💌
	ff
	1
文件先型(T): Audio File(*, mp3, *, way. *, aac) ▼ Unaw	Cancel ( <u>N</u> )

9, Input at lease one receiving phone number or e-mail address.

Custom Information Setting					
Admin Number :	Rece	ive Email 1 : Bolytest	@bolymedia.com		
Phone Number 2 :	Rece	ive Email 2 :			
Phone Number 3 :	Rece	ive Email 3 :			
Phone Number 4 :	Rece	ive Email 4 :			
Attention Please ,The Data Above Will Be Saved In The Following File:					
F:\GSM\MG982K.TXT			-		
SAVE	ΞW	E×IT ( <u>N</u> )			

10, Save this .txt file into your SD card in camera.