

Cobra[®] microTALK

LICENCE FREE
MT 200-2VP EU

Walkie Talkie
Recetrasmittitore
Handfunkgerät
Transceptor
Talkie Walkie

COMMUNICATES
WITH ALL OTHER
PMR 446 RADIOS



Radios shown
actual size
and have a
1 year warranty



















16 LANGUAGE
INSTRUCTION MANUAL



Nothing Comes Close to a Cobra[®]

8 Channels | LCD Display | Call Alert
Roger Beep | Battery/Power Saver | Auto Squelch
Battery Low Indicator | 6 AAA NiMH Rechargeable Batteries
"Y" Wall Mount Charger

Cobra[®] MT 200-2VP EU LICENCE FREE **microTALK** **Walkie Talkie**

FEATURES	BENEFITS	SPECIFICATIONS
UHF/FM	Ultra-clear long distance reception.	Unit Dimensions 50.8 mm H x 127.5 mm W x 39 mm D (2.0" H x 5.02" W x 1.54" D) including antenna
5 KM Range	Up to 5 KM range. (Range will vary depending on terrain and conditions).	Unit Weight 65 g (2.22 oz) Without batteries
8 Channels	Front panel push buttons provide easy access to all 8 channels.	RF Output 500 mW
Battery Saver Circuitry	A unique circuit extends the life of the batteries. If there are no transmissions within 10 seconds, the unit will automatically switch to battery saver mode.	Channels 8 CH 1 = 446.00625 MHz 2 = 446.01875 3 = 446.03125 4 = 446.04375 5 = 446.05625 6 = 446.06875 7 = 446.08125 8 = 446.09375
Call Alert	Provides an easily recognizable alert for incoming calls.	SKU# MT 200-2 VP EU
Roger Beep Tone	Confirmation tone indicates the completion of the user's transmission, and signals to others it is clear to talk.	Batteries 3 AAA NiMH rechargeable batteries per radio included.
Auto Squelch	Automatically shuts off weak transmissions or unwanted noise due to terrain or range constraints.	UPC 0-28377-90711-1
LCD Display	Easy to view display provides the radio's status at a glance.	Master Pack Barcode 100 28377 90711 8
Keystroke Tone Signal	Confirms key activation.	Individual Blister Dimensions 207.1 mm H x 256.7 mm W x 91.4 mm D (8.15" H x 10.10" W x 3.6" D)
Battery Low Indicator	Blinks when battery power level is low.	Individual Blister Weight 591 g. (20.84 oz.)
Speaker/Microphone/Charge Jack	Allows use of "Y" wall mount charger or earphone speaker/microphones (not included) for "hands-free" operation	Master Pack Quantity 4
Multilingual Manual	Includes a 16 language instruction manual.	Master Pack Dimensions 284.2mm H x 258.7mm W x 101mm D (11.19"H x 10.19" W x 4" D)
Belt Clip	Secures your microTALK radio while on the go.	Master Pack Weight 2,964g (104.550 oz.)
No Licence or Service Fees	High quality band frequencies with no fees.	Specifications subject to change without notice.
INCLUDED ACCESSORIES		MANUAL LANGUAGES
6AAA NiMH Rechargeable Batteries	Radios can also be used with 3AAA Alkaline batteries (not included)	 English  Hungarian
"Y" Wall Mount Charger	Charges supplied rechargeable batteries inside radios. Charges one or two radios. 230V/2-pin EU Plug.	 Czech  Italian
		 Danish  Norwegian
		 Dutch  Polish
		 Finnish  Portuguese
		 French  Romanian
		 German  Spanish
		 Greek  Swedish

Nothing Comes Close to a Cobra[®]

Cobra[®], microTALK[®], Nothing Comes Close to a Cobra[®] and the snake design are registered trademarks of Cobra Electronics Corporation, USA. Cobra Electronics Corporation[™] is a trademark of Cobra Electronics Corporation, USA. CEEL[™] is a trademark of Cobra Electronics Europe LTD.